Avaya Aura Messaging (Voice Mail)

Voice Mail Commands page for commands available while manuevering through the system

Anytime	 ④ Skip/ Enter/ bypass a greeting/ interrupt a prompt ● Help ★ Cancel or backup one menu 	
 Review Messages 2 Read 3 Saved 4 Delete pending messages 	During Message (1) Rewind (a few sec) (1) (1) Rewind to start (2) Pause/ Resume (3) Fast Forward (a few sec) (3) (3) Fast Forward to end (4) Slow Playback (5) Fast Playback (6) Fast Playback (6) (6) Fastest Playback (7) Delete #Skip to the next message	After Message ④ Replay ⑤ Message Details ⑥ Forward (with intro) ⑥ ① Forward (without intro) ⑥ ⑥ Forward (rmv prev intros) ⑦ Delete ⑧ Reply ⑧ ⑧ Call Sender ⑨ Save # Skip to the next message
② Send Messages	Step 1: Record Message when finished press # Step 2: Address Message • Enter a mailbox number • Spell a name or distribution list • Say a name or distribution list	 Hear delivery options Private Private Private Private Add more recipients Cancel Send
(User Preferences	 1 Features 1 Notify Me (on/off) (*Must be configured by administrator) 2 Reach Me (on/off) (*Must be configured by administrator) 3 Auto Log in (on/off) (*Must be configured by administrator) 4 Message Blocking 2 Administrative Options 2 1 Password 3 Date and time paycheck (on/off) (*default is set to on) 3 Greetings 3 Personal Greeting 3 2 Record personal greeting 3 2 2 Away from phone (*Must be configured by administrator) 3 2 Extended absence (*Caller cannot skip greeting) 3 Amme 3 Activate optional greeting 3 Activate optional greeting 	
6 Restart *Exit		

ACCESSING VOICE MAIL

- From a phone on the system
 - Dial voice mail extension (600) or press the Messages key.
 - At the prompt press # (to access your mailbox)
 - Enter password followed by the # key. (86245 = temporary password).
- From an outside line
 - Dial **455-0600**, the direct number to voicemail, you reach the system greeting.
 - -or- Dial your DID number to reach your greeting.
 - During your greeting, press * *, to get to the system greeting.
 - At the system greeting press the # key.
 - Enter your 7-digit mailbox number followed by the # key.
 - Enter your password followed by the # key.

HOW TO LEAVE A VM WITHOUT RINGING PHONE

- Access Voicemail system (press messages button or dial VM extension)
- At the prompt, dial the 7-digit mailbox number of the party you wish to leave a message for.

Note: You can also transfer a caller into someone's voicemail by using the above with the transfer feature.

HOW TO TRANSFER TO VM WITHOUT RINGING PHONE

- After you receive a call on your line, press the "Transfer" soft key
- Press the Msg/Inbox key
- Press * at any time to get to the system greeting
- The voice message will ask you for the mailbox number. Enter the 7-digit mailbox number for the party you wish to leave a message for (without the # at the end)
- Press the "Transfer" soft key

NOTES:

- The voice mail system assumes you are the owner of the extension you are calling from and will ask you for the password.
- The voice mail system has voice prompts that will walk you through the system.
- You will be forced through an enrollment process the first time you log in to the system (Change Password, Record Name, Select Greeting -Standard System Greeting / Personal Greeting).
- Your temporary password is **86245**.
- Minimum password length is 4-digits, trivial passwords are not allowed.
- To bypass a greeting or interrupt a prompt, press #.
- Passwords do not expire.
- You can have up to six invalid login attempts then your mailbox will be disabled. You can have three invalid login attempts per session.